

## Таблица переводов измерений

dBm	dBV	V вольт	W Вт на 50 Ом
40	26,99	22,36068	10
35	21,99	12,57433	3,16228
30	16,99	7,071068	1
25	11,99	3,976354	0,31623
20	6,9897	2,236068	0,1
13	-0,01	0,998815	0,01995
10	-3,01	0,707107	0,01
5,	-8,01	0,397635	0,00316
0	-13,01	0,223607	0,001
-10	-23,01	0,070711	0,0001
-20	-33,01	0,022361	0,00001
-30	-43,01	0,007071	1E-06
-40	-53,01	0,002236	1E-07
-50	-63,01	0,000707	1E-08
-60	-73,01	0,000224	1E-09
-70	-83,01	7.07E-05	1E-10
-80	-93,01	2.24E-05	1E-11
-90	-103	7.07E-06	1E-12
-92	-105	5.62E-06	6.3E-13
-94	-107	4.46E-06	4E-13
-96	-109	3.54E-06	2.5E-13
-98	-111	2.82E-06	1.6E-13
-100	-113	2,24E-06	1E-13
-102	-115	1.78E-06	6.3E-14
-104	-117	1,41E-06	4E-14
-106	-119	1.12E-06	2,5E-14
-108	-121	8.9E-07	1.6E-14
-110	-123	7.07E-07	1E-14
-112	-125	5.62E-07	6.3E-15
-114	-127	4.46E-07	4E-15
-116	-129	3.54E-07	2,5E-15
-118	-131	2,82E-07	1.6E-15
-120	-133	2.24E-07	1E-15
-122	-135	1.78E-07	6,3E-16
-124	-137	1.41E-07	4E-16
-126	-139	1.12E-07	2.5E-16
-128	-141	8.9E-08	1.6E-16
-130	-143	7.07E-08	1E-16